

**Statement Of Work
For
REBUILD OF AMPLIFIER ASSEMBLY, AM-6545B/GRC-193B(V)
NSN 5895-01-270-5095
P/O AN/GRC-193B**

SOW-03-847-2-8D865B-1/1

**Prepared by
Life Cycle Management Center, Code 847-2
Marine Corps Logistics Bases, Albany, GA.**

Table of Contents

Section/Para	Page
1.0 Scope	1
1.1 Background	1
2.0 Applicable Documents	1
2.1 Military Standards	1
2.2 Other Government Documents and Publications	1
2.3 Industry Standards	2
3.0 Requirements	3
3.1 General Tasks	3
3.2 Detail Tasks	3
3.2.1 Phase I - Pre-Induction	3
3.2.2 Phase II - Rebuild	3
3.2.3 Phase III - Inspection, Testing and Acceptance	4
3.2.4 Packaging, Handling, Storage, and Transportation (PHS&T)	4
3.3 Configuration Control	4
3.4 Government Furnished Equipment (GFE)/ Government Furnished Materiel (GFM)	4
3.5 Contractor Furnished Materiel	5
3.6 Electrostatic Discharge (ESD) Control Program	5
3.7 Electromagnetic Environmental Effects (E ³) Procedures	5
3.8 Quality Assurance Provisions	5
3.9 Acceptance	5
3.10 Rejection	5
Appendix A	A-1

STATEMENT OF WORK FOR THE
AMPLIFIER ASSEMBLY, AM-6545B/GRC-193B(V)
NSN 5895-01-270-5095
P/O AN/GRC-193B

1.0 Scope. This Statement of Work (SOW) establishes and sets forth tasks and identifies the work efforts that shall be performed by the Contractor (for purposes of this SOW, Contractor is defined as the commercial or government entity performing the rebuild) in the rebuild effort of the Amplifier Assembly. This document contains requirements to restore the Amplifier Assembly to Condition Code "A." Condition Code A is defined as "serviceable/issuable without qualification, new, used, repaired or reconditioned materiel which is serviceable and issuable to all customers without limitation or restriction, including materiel with more than 6 months shelf-life remaining."

1.1 Background. Rebuild is defined as: "That maintenance technique to restore an item to a standard as near as possible to original or new condition in appearance, performance, and life expectancy. This is accomplished through a maintenance technique or complete disassembly of the item, inspection of all parts or components, repairs or replacement of worn or unserviceable elements using original manufacturing tolerances and/or specifications and subsequent reassembly of the items."

2.0 Applicable Documents. The following documents form a part of this SOW to the extent specified. Unless otherwise specified, the issues of these documents are those listed in the Department of Defense Index of Specifications and Standards (DoDISS) and supplement thereto which is in effect on the date of solicitation. In the event of conflict between the documents referenced herein and the contents of the SOW, the contents of this SOW shall be the superseding requirement.

2.1 Military Standards.

MIL-STD-129	DoD Standard Practice for Military Marking
MIL-STD-2073-1D	DoD Standard Practice for Military Packaging

2.2 Other Government Documents and Publications. The issues of those documents cited below shall be used.

<u>Short Title</u>	<u>Long Title</u>
TM-07749B	Operators and Organizational Maintenance Manual For AN/GRC-193B(V)
TM-07749B-12/1	General Support, Direct Support Maintenance and Depot Maintenance Manual for AN/GRC-193B(V)
SL-4-09213A	Repair Parts List for AN/GRC-193B
TM-08446A-50/2 M/S	ERRATUM

TM-4750-15/2	Painting and Registration Marking for Marine Corps Combat and Tactical Equipment
TI-5820-25/22	Electromagnetic Environmental Effects (E ³) Procedures For Installation of Communication Equipment on U.S. Marine Corps Platforms
Engineer Drawing 755017C3000 Cage 01365	Power Amplifier, AM/6545B/GRC-193B
DOD 4000.25-1-M	MILSTRIP Manual
NAVICPINST 4491.2A	Requisitioning of Contractor Furnished Material From The Federal Supply System

Military Handbooks (For Guidance).

MIL-HDBK-61	Configuration Management Guidance
-------------	-----------------------------------

2.3 Industry Standards

ANSI/ISO/ASQC Q9003-1994	Quality Systems - Model for Quality Assurance in Final Inspection and Test
JESD625-A	Requirements for Handling Electrostatic-Discharge-Sensitive (ESDS) Devices

Industry Standards (For Guidance)

ANSI/EIA-649	National Consensus Standard for Configuration Management
--------------	--

Copies of Military Standards and Specifications are available from the DOD Single Stock Point, Document Automation and Production Service, Building 4/D, 700 Robbins Avenue, Philadelphia, PA 19111-5094, Telephone (215) 697-2179 or DSN 442-2179, or <http://www.dodssp.daps.mil>. Copies of other government documents and publications required by contractors in connection with specific SOW requirements shall be obtained through the contracting officer: Commander, Marine Corps Logistics Bases, (Code 891) Attn: Contracting Officer, 814 Radford Blvd., Albany, Georgia 31704-1128, commercial telephone number (229) 639-6773 or DSN 567-6773. Copies of engineering drawings, if applicable, shall be obtained from Life Cycle Management Center, Attn: Code 851-3, 814 Radford Blvd. STE 20320, Albany, Georgia 31704-0320, commercial telephone number (229) 639-6410 or DSN 567-6410.

3.0 Requirements.

3.1 General Tasks. In fulfilling the specified requirements, the Contractor shall:

a. Provide materials, labor, equipment, facilities and missing/repair parts, necessary to inspect, diagnose, restore, and test and calibrate the Amplifier Assembly. Upon completion of rebuild, the subject item shall be Condition Code "A."

b. Conduct in-process and final on-site testing for witness by a Marine Corps (Code 847-2) authorized representative.

3.2 Detail Tasks. The following tasks describe the different phases for rebuild of the Amplifier Assembly.

3.2.1 Phase I - Pre-Induction. The contractor shall perform a pre-induction inspection analysis for each Amplifier Assembly using the Contractor Facility's diagnosis, inspection and testing techniques to determine extent of work and parts required. These findings shall be annotated on the Pre-Induction Checklist (Appendix A).

3.2.2 Phase II - Rebuild. After pre-induction tests and inspections have been completed, repair of the Amplifier Assembly shall be accomplished by the contractor in accordance with this SOW. Deficiencies noted on the Pre-Induction Checklist (Appendix A) during Phase I shall be repaired/replaced. Components or assemblies shall not be disassembled for replacement of parts unless that part has failed, or the component assembly wherein the part is located is disassembled for repair. Any Modification Instructions (MIs) or Engineering Change Proposals (ECPs) not previously applied shall be incorporated.

a. Hardware.

(1) Replace broken, unserviceable and/or missing hardware including nuts, bolts, screws, washers, turn lock fasteners, mandatory replacement items, safety, and one-time use items, etc., in accordance with this SOW. Unserviceable would include any of the above that failed to function properly.

(2) Ensure proper hardware locking devices are present on all moving mechanical assemblies.

(3) Hardware normally supplied with commercial parts shall be used unless specifically prohibited.

3.2.3 Phase III - Inspection, Testing and Acceptance.

a. The contractor shall conduct Inspection, Testing and Acceptance of the Amplifier Assembly in accordance with this Statement of Work, TM-07749B, TM-07749B-12/1, SL-4-09213A, TM-4750-15/2, TI-5820-25/22, Engineer Drawing 755017C3000, and TM-08446A-50/2 M/S ERRATA.

b. The Contractor shall be responsible for conducting required tests and shall ensure all necessary personnel are notified prior to completion of the final acceptance. Acceptance tests shall be held at the Contractor's facility. MCLB, Code 847-2, Albany, Georgia representatives shall be given a minimum of two weeks notice prior to commencement of acceptance testing.

c. The Contractor shall be responsible for correcting any deficiencies identified during inspection/testing. MCLB, Code 847-2, Albany, Georgia representatives may require the Contractor to repeat tests or portions thereof, if the original tests fail to demonstrate compliance with this SOW.

3.2.4 Packaging, Handling, Storage and Transportation (PHS&T).

a. The Contractor shall be responsible for preservation and packaging of equipment being repaired under the terms of this statement of work. Items being prepared for long term storage or shipment to overseas destinations shall be preserved and packaged in accordance with the level "A" requirements of MIL-STD-2073-1D, Appendix A, Table A.VI., Electronic Equipment. Items being prepared for domestic shipment and immediate use shall be to level "B" requirements.

b. Marking shall be in accordance with MIL-STD-129.

c. The Marine Corps will provide the Contractor with the shipping address(es) for delivery of the repaired equipment. The contractor shall be responsible for arranging for shipment to the pre-designated site(s). The Marine Corps will be responsible for transportation costs associated with shipping the subject equipment to and from the Contractor.

3.3 Configuration Control. The contractor shall apply configuration control procedures to established configuration items. The contractor shall not implement configuration changes to an item's documented performance or design characteristics without prior written authorization. If it is necessary to temporarily depart from the authorized configuration, the contractor shall prepare and submit a Request for Deviation. MIL-HDBK-61, (paragraph 4.3 and Table 4-9) and ANSI/EIA-649 (paragraph 5.3.4) provide guidance for preparing this configuration control document.

3.4 Government Furnished Equipment (GFE)/Government Furnished Materiel (GFM). GFE is government owned equipment authorized by contract for use by a Commercial/Government Contractor. It is neither consumed during production nor incorporated into any product. GFM is materiel furnished to a contractor that will be consumed during the course of production or incorporated into the product being manufactured/remanufactured under a contract/statement of work. In the event the Marine Corps does have GFE/GFM requirements the Management Control Activity (MCA/827-2), Marine Corps Logistics Bases, Albany, Georgia, will coordinate required GFE and will maintain a central control on Marine Corps assets in the Contractor's possession. The MCA will forward a GFE Accountability agreement to the Contractor Facility for signature to establish a chain of custody and property responsibilities for Marine Corps assets.

3.5 Contractor Furnished Materiel. The Marine Corps has adopted the Navy's procedures regarding Contractor Furnished Materiel (NAVICPINST 4491.2A). In the event that Contractor Furnished Materiel is required for repair parts, the Contractor shall requisition through the DoD Supply System. DoD 4000.25-1-M, (MILSTRIP) Chapter 11 authorizes contractors to requisition through the DoD Supply System.

3.6 Electrostatic Discharge (ESD) Control Program. The contractor shall establish, implement and document an ESD control program following the guidelines provided in JESD625-A. ESD protective measures shall be used during manufacturing, handling, inspection, test, marking, packaging, storing and transporting ESD sensitive components.

3.7 Electromagnetic Environmental Effects (E³) Procedures. The Contractor shall plan for and use proper (E³) control procedures in the rebuild process and shall utilize TI-5820-25/22 in conjunction with the detailed requirements specified in this document.

3.8 Quality Assurance Provisions. The Contractor shall provide and maintain a minimum, adheres to the requirements of ANSI/ISO/ASQC Q9003-1994, Quality Systems - Model for Quality Assurance in Final Inspection and Test. The program shall ensure quality throughout all areas to include, processing, assembly, inspection, test, maintenance, and preparation for delivery and shipping. Unless otherwise specified in the contract, the Contractor shall be responsible for performance of all inspection requirements. The Government reserves the right to perform any of the inspections set forth in the contract where such inspections are deemed necessary to assure products and services conform to the prescribed requirements. The contractor shall provide an Inspection and Test Plan that will ensure the Amplifier Assembly will meet or exceed the original performance characteristics of the Amplifier Assembly.

3.9 Acceptance. The performance of the Contractor and the quality of work delivered, including all equipment furnished and documentation written or compiled, shall be subject to in-process review and inspection during performance. Inspection may be accomplished in-plant or at any work site or location, and Marine Corps (MCLB, Code 847-2) representatives shall be permitted to observe the work or to conduct an inspection. Final inspection and acceptance testing shall be conducted at the Contractor's Facility. Final acceptance shall be conducted on 100 percent of items to verify that the units meet all requirements.

3.10 Rejection. Failure to comply with any of the specified requirements listed herein shall be reason for rejection by MCLB, (Code 847-2), Albany, representative. The Contractor shall, at no additional cost to MCLB, Albany, Georgia, correct the deficiencies and repeat the verification until an acceptable compliance with acceptance test procedures is demonstrated.

Pre-Induction Checklist
Amplifier Assembly, AM-6545B/GRC-193B(V)
P/O AN/GRC-193B

1. Inspect for dirt, dust, sand, etc.
2. Inspect for rust and/or corrosion damage.
3. Inspect for any physical damage to unit, cuts, dents, cracks, or broken pins.
4. Ensure that all screws, washers, nuts, bolts, etc. are attached.
5. Inspect for dry rot.

S - Serviceable U - Unserviceable M - Missing

<u>Amplifier Assembly AM-6545B Inventory /Serviceability check:</u>	<u>Condition</u>	<u>Remarks</u>
1. Meter, RF	_____	_____
2. 400W-100W Switch	_____	_____
3. Ready (RDY) Light	_____	_____
4. Transmit (XMT) Light	_____	_____
5. Tune (TUN) Light	_____	_____
6. Fault Light, Filament (FIL)	_____	_____
7. Fault Light, Power Amplifier (PA)	_____	_____
8. Fault Light. Coupler (CPLR)	_____	_____
9. Circuit Breaker (PA CB)	_____	_____
10. Antenna Coupler Circuit Breaker (ANT CPLR CB)	_____	_____
11. Fan/Lamp Test Switch	_____	_____
12. Connector, RT RF, J5	_____	_____
13. Connector, RT CONT, J2	_____	_____
14. Connector, RT DC PWR, J3	_____	_____
15. Connector, RF, J4	_____	_____
16. Connector PA-CPLR, J1	_____	_____

APPENDIX A

